

# Dräger REGARD Master Control card

A system Master card which supervises up to 99 input channels. Offers common, single and voting alarms and a remote system reset input.



D-15086-2009

The Dräger REGARD System Master card is used when other cards within the system required unique addresses. All voting, grouped and common alarm status are repeated by the Master card. The Master card can be utilised to Automatically or Copy system configurations to and from a programming PC. Additional Master cards (Xtra) can be installed into a system to give additional voting, grouped or common alarms.

## FEATURES AND BENEFITS

- Voting/Grouped alarm outputs
- Common alarm outputs
- Fully configurable
- Simple operation
- Password protected
- Up to fifteen Xtra Master cards per system



ST-390-2004

Dräger REGARD Master

## TECHNICAL DATA

Control card	Local alphanumeric display Front panel push buttons Front panel LED's
Inputs	RS 485 (internal) Remote reset
Outputs	R1, R 2, and R 3 alarm relays
Power Supply	24 V DC,125 mA
Communications	Internal system highway using RS 485
Approvals	Tested to EN 50270 for EMC directive ATEX II (2)G Acc. to Directive 94/9/EC
Safety Integrity Level	SIL2 certified by exida (IEC 61508)

## ORDER INFORMATION

Dräger REGARD Master	42 05 702
Dräger REGARD Master (DMT)	42 06 307
Dräger REGARD Master (ATEX)	42 06 708



Thank you for reading this data sheet.

For pricing or for further information, please contact us at our UK Office, using the details below.



**UK Office**

**Keison Products,**

**P.O. Box 2124, Chelmsford, Essex, CM1 3UP, England.**

**Tel: +44 (0)330 088 0560**

**Fax: +44 (0)1245 808399**

**Email: [sales@keison.co.uk](mailto:sales@keison.co.uk)**

Please note - Product designs and specifications are subject to change without notice. The user is responsible for determining the suitability of this product.